
RF Touch Dimmer

Technische Daten	
Input Voltage	5 - 24 Volt DC
Wattage	max. 36 Watt at 12 Volt DC input max. 72 Watt at 24 Volt DC input
Туре	500 mm mains lead with LED plug-in connection 500 mm lead with LED socket 2000 mm sensor lead with Ringterminal M4
Dimensions	99 x 47 x 12 mm
Housing colour	white
Installation	with screws
Radio range	$\max.\ 15\ m$ in open area, might be reduced greatly by metal or walls
Remarks	installation on secondary side between transformer and light, wireless connection between two or more touch controllers, synchronous switching and dimming of the attached lights, setup of 4 separate control channels possible





Article code

39.418.000